

# Security & Control Panel

2GIG-GC2E-345



## Your Favorite Panel Just Got Better

2GIG sets the standard for exceptional performance that delivers true peace of mind. With our GC2e, enjoy the proven performance and trustworthiness of the original 2GIG GC2 panel, along with new features that make life as a dealer even easier. With improvements like eSeries encrypted compatibility, an entirely new sleek design, larger capacitive touch screen, and our best-in-class 2-way voice, homeowners and dealers alike will appreciate the peace of mind they get from their 2GIG GC2e experience.

### Key Selling Points:

- Enlarged, brighter 5" screen for better viewing and user experience
- eSeries encrypted sensors provide enhanced security
- Enhanced user interface with capacitive touch technology
- Elegant industrial design that blends in with today's lifestyle
- Expanded smart home ecosystem with Z-Wave Plus and S2 encryption
- Exceptional field-proven reliability and performance

### Features You Love:

- Installer programming features and flow stay the same
- Backward compatible with all GC2 sensors for easy upgrades
- Supports LTE 4G and 3G radios
- Alarm.com and SecureNet compatible

# 2GIG SECURITY & CONTROL PANEL SPECIFICATIONS & TECHNOLOGY

## eSeries™

### NEW FEATURES




#### 5" Capacitive Touch Screen

Larger, more responsive screen enhances the user experience.



#### eSeries Sensors

New eSeries encrypted sensors provide enhanced security while reducing the risk of takeovers.



#### Easy Upgrades

Support for traditional 2GIG and other legacy 345 sensors makes system upgrades easy.



#### Front-Firing Speaker

Front-firing speaker delivers exceptional audio performance.



#### Two-Way Voice

Best-in-class voice quality provides worry-free communication with monitoring services, police/fire.



### Control From Anywhere



### Panel

- 5" capacitive touchscreen
- Intuitive User Interface
- Quick Arm
- Dedicated Home & Emergency Buttons

### Security

- eSeries Sensors
- 60 Wireless Zones
- 1 Wired Zones
- 8 Keyfobs
- 4 Keypads
- Wired Bell Output
- 64 Users

### Communication

- Replaceable cell radio with snap-on antenna
- 4G LTE – Verizon and AT&T Network
- 3G – AT&T or Rogers Network
- CDMA – Verizon Network

### Automation

- Integrated Z-Wave Plus radio with S2 Security
- Supports up to 232 Z-Wave devices
- Create and execute Scenes

### Installation

- Third-hand strap
- Integrated level
- Easy-to-align center mark
- Same programming as GC2

### Accessories

- 2GIG Intrusion Sensors
- 2GIG Life Safety Sensors
- 2GIG Notification Sensors
- 2GIG TS1
- GoControl Z-Wave Compatible Products

See <https://www.2gig.com/products/> for complete line of accessories

### Power

- 100-240VAC 50/60Hz 1.7A 14VDC adapter
  - Ni-MH backup battery: 2000 mAH (included), 2400 mAH (optional)
- Operating Temperature:** 32°F to 104°F (0°C to 40°C)

### Certifications

- UL985, UL1023, UL1635, UL1610
- ULC C1023, ULC S545-02 (Canada)
- ANSI/SIA CP-01 2010
- CSFM

### Warranty

**Panel warranty:** Limited 3 years

### Ordering Information

- Panel: 2GIG-GC2E-345
- Kits: 2GIG-GC2E-345-K41, 2GIG-GC2E-345-K31

### Firmware Updates

- Over-the-air
- Update Tool
- PC Update Tool